
Hi-Limit programming

Code Protected Parameters Access:

- Press SET and hold for 8 seconds. The access code value 0 is shown on the display. With the UP and DOWN arrows, enter the access code (unit comes with access code set at 83 OR 0).
- Press SET to enter the code. If the code is correct, the first parameter label will be shown on the display (SP).
- Move to the desired parameter with the UP and DOWN arrows.
- Press SET to view the value on the display.
- Use the UP and DOWN arrows to modify the parameter value.
- Press SET to save the value and exit the parameter.
- Repeat until all necessary parameters are modified.
- Press SET and DOWN at the same time to quit the programming mode, or wait one minute and the display will automatically exit programming mode.

The setting values for the GEN3 oven:

SP: 800
R0: 1
R1: 0
R2: 800
R3: hoL
D0: Hi
C0: 1
C2: On
C3: YES
P1: 0
P5: TCj
P6: 0
HI: Pu
H5: 83 OR 0 (Access code)